

# Servo amplifier

## mcDSA-E62

Article number: 1505024



Picture similar

### Technical data

| Supply voltages                                 |                               |
|---|-------------------------------|
| Electronic supply voltage $U_e^{*1}$            | 9..30 V                       |
| Electronic current consumption @ $U_e=24V^{*2}$ | typ. 30 mA                    |
| Power supply voltage $U_p^{*3}$                 | 9..60 V                       |
| Output current                                  |                               |
| Max. output current                             | 15 A                          |
| Continuous output current @ $U_p=24V^{*4}$      | 5 A                           |
| Continuous output current @ $U_p=48V^{*4}$      | 4.3 A                         |
| PWM   |                               |
| Output voltage                                  | 90% $U_p$                     |
| PWM frequency                                   | 25, 32 <sup>*5</sup> , 50 kHz |
| Mechanical                                      |                               |
| Size LxWxH                                      | 74 x 45 x 17 mm               |
| Weight  | 30 g                          |
| Environment                                     |                               |
| Protection class                                | IP20                          |
| Ambient temperature (operation)                 | -25..70 °C                    |
| Ambient temperature (storage)                   | -25..85 °C                    |
| Rel. humidity (non-condensing)                  | 5..90 %                       |
| CAN bus   |                               |
| Protocol  | DS301                         |
| Device profile                                  | DS402                         |
| Max. baudrate                                   | 1 Mbit/s                      |
| CAN specification                               | 2.0B                          |
| Galvanically isolated                           | no                            |
| Sensor supply (Encoder)                         |                               |
| Output voltage                                  | 5 V                           |
| Max. output current                             | 0.2 A                         |

| Encoder                   |  |
|---------------------------|--|
| Type                      | sin / cos                              |
| Signals                   | +Sin,-Sin,+Cos,-Cos                    |
| Resolution                | 13 bit per sine period                 |
| Input voltage             | 1 V peak-peak, differential            |
| Signal type               | sine/cosine, analog, differential      |
| Digital inputs            |  |
| Number (+/-30V tolerant)  | 2 (Din0..1)                            |
| Number (0..30V tolerant)  | 1 (Din2)                               |
| Low voltage               | 0..5 V                                 |
| High voltage              | 8..30 V                                |
| Notice                    | Din2 parallel with Dout0 <sup>*6</sup> |
| Digital outputs           |  |
| Number                    | 1 (Dout0)                              |
| Continuous output current | 1.5 A                                  |
| Load                      | resistive, inductive                   |
| Output voltage            | Electronic supply voltage $U_e$        |
| Signal type               | positive switching                     |
| Notice                    | Dout0 parallel with Din2               |
| Analog inputs             |  |
| Number                    | 1 (Ain0)                               |
| Signal type               | 0..10 V, 12 Bit, single ended          |

\*1 No reverse polarity protection, the destruction limit is at overvoltage of  $\geq 33V$  or short-term peak voltage of  $37V < 1s$

\*2 power amplifier switched off, 5V output (sensor supply) is free

\*3 No reverse polarity protection, the destruction limit is at overvoltage of  $\geq 80V$

\*4 connector cable with max. possible cable cross-section, PWM frequency 32 kHz, ambient temperature 40 °C ( $t > 40$  °C derating), RMS current: 5 A  $\rightarrow$  4.1 Aeff, 4.3 A  $\rightarrow$  3.5 Aeff

no guarantee, since value is determined empirical, please consider the application notes to determine the continuous current

\*5 default value

\*6 Input voltage must not exceed Electronic supply voltage  $U_e$

Additional technical data are available in mcManual.



## Scheme



©2023 by miControl

## Terminal assignment

| X1 Encoder, I/O's and CAN |            |   |
|---------------------------|------------|---|
| 1                         | GND        | Ground for sensor supply<br>Notice: don't connect with system GND |
| 2                         | +U5V       | 5V output voltage for sensor supply<br>Sensors: encoder           |
| 3                         | +Cos       | Encoder, plus cosine signal                                       |
| 4                         | +Sin       | Encoder, plus sine signal   |
| 5                         | res.       | Reserved  |
| 6                         | -Cos       | Encoder, minus cosine signal                                      |
| 7                         | -Sin       | Encoder, minus sine signal  |
| 8                         | CAN Lo     | CAN Low   |
| 9                         | CAN Hi     | CAN High  |
| 10                        | Din2/Dout0 | Digital input 2 / Digital output 0                                |
| 11                        | Din1       | Digital input 1   |
| 12                        | Din0       | Digital input 0   |
| 13                        | Ain0       | Analog input 0  |
| 14                        | GND        | Ground for electronic supply voltage                              |
| 15                        | +Ue        | Electronic supply voltage   |
| X2 Motor                  |            |   |
| 1                         | +Up        | Power supply voltage  |
| 2                         | GND        | Ground for power supply voltage                                   |
| 3                         | Ma         | Motor phase A   |
| 4                         | Mb         | Motor phase B   |
| 5                         | Mc         | Motor phase C   |